H Series Isolator

Nanjing New Power Electric Co., Ltd.

➔ Introductions

This isolator converts the current/voltage signals into current/voltage signals, and also provides transmitters with power in the field. Current input isolator allows transmission of HART communication signals.

The input, output, and power supply are galvanically isolated from each other. The main advantages of the isolator are fast response, low dissipation and temperature stability. It can be interfaced with all kinds of device, such as DCS, PLC and other systems.

➔ Parameters

Power supply (13, 14):

Rated voltage: 18 V DC ~ 32 V DC (Recommended voltage: 24 V DC)

Input (1, 2, 3; 4, 5, 6):

Current: 0(4) ~ 20 mA; 0 ~ 10 mA

Voltage: 0(1) ~ 5 V; 0 ~ 10 V (Please see the product label for details)

Input resistance:

Current: Approx. 50 Ω

Voltage: ≥ 1 MΩ

Available voltage:

Open-circuit voltage ≤ 27 V, voltage: ≥ 22 V at 20 mA

Output (8, 9; 11, 12):

Sink mode: 4 ~ 20 mA

Output current: 0(4) ~ 20 mA; 0 ~ 10 mA

Output voltage: 0(1) ~ 5 V; 0 ~ 10 V

Other signal types is required special customization, please see the product label for details

Load resistance:

Sink mode: $R_L \leq [(U-3)/0.02]$ Ω U: Loop power supply

0(4) ~ 20 mA: ≤ 450 Ω; 0 ~ 10 mA: ≤ 900 Ω

0(1) ~ 5 V: ≥ 1 MΩ; 0 ~ 10 V: ≥ 2 MΩ

Other load resistance is required special customization, please see the product label for details.

Transmission characteristics:

Accuracy: ± 0.1% F.S. (25 ℃ ± 2 ℃)

Response time: ≤ 2 ms

Temperature drift: 0.005%F.S./℃

Electromagnetic compatibility: According to IEC 61326-3-1

Dielectric strength (1 mA leakage current, 1 minute test time):

≥ 1500 V AC (Input /Output, Input /Power supply)

≥ 500 V AC (Power supply / Output)

Website: http://www.anpe.cn
Service Tel: +86(25)-84459479
Address: New Power industrial Park, Luhe Economic Development Zone, Nanjing, China
Postcode: 211500

Website: http://www.anpe.cn
Service Tel: +86(25)-84459479
Address: New Power industrial Park, Luhe Economic Development Zone, Nanjing, China
Postcode: 211500